


Technical Data

Voltage rating: 220V AC 50/60Hz
 Voltage limit: 180V-250V AC
 Hysteresis: ≤ 1 sec/day (25%)
 ON/OFF Operation: 16 On & 16 Off
 Power Consumption: 2VA (max.)
 Display: LCD
 Service life: Mechanical 10⁷
 Electrically 10⁵
 Minimum Interval: 1 minute
 Weight: approx. 60g
 Countdown: 1 sec – 99min 56 sec
 Pulse: 1 sec – 99 min 59 sec
 Load capacity:
 - Resistive load– 16A/250V AC
 - Lagging load – 10/250V AC
 - Lamp load – 2000W
 Switching contact: 1 changeover switch
 Power reserve: 3 years (Lithium battery)
 Ambient temperature: -10~+40°C
 Ambient humidity: 35~85% RH

DIN Rail Installation

- Advanced pre-setting one week before
- Digital electronic time switch with daily programs
- Repeat programs with 16 on/off setting and manual over-ride
- Lithium battery power reserve
- Auto time error correction ± 60 seg., weekly

Display



1		TIMER
2	D +	DATE
3	H +	HOURL
4	M +	MIN
5		CLOCK
6	C	RESET
7	MANUAL	MANUAL

Operating Instruction

1. To start switch: Press reset Key. At the first time, if you want to set to the present time, please press “Clock” on board, then press D +, H +, M + to adjust the number to the present time
2. Enter into programming as below:

Step	Key	Programming
1	Press	Setting 1 ON (Display 1 ON)
2	Press H + / M+	Setting hours and minutes
3	Press D +	To select same configuration everyday, or different times each day
4	Press	Setting 1 OFF (Display 1 OFF)
5	Press H + / M+	Setting hours and minutes to turn off
6	Press D +	If you want the same everyday, you don't need to press this key
7	Repeat steps 2 - 6	Set programs 2 – 6 on and off time
8	Press	End – If you do not require 16 setting press “” to the end

Notes:

1. Time setting should be according to the time sequence, can't be set crossly.
2. System will quit automatically if there isn't no operating within 10 seconds and no data is saved.
3. Functions 3, 4 and 5 can't be used simultaneously.